

User Guide - FLCT4BS

RF Control - 4 Zone Touch Remote



Features

- For use with all Single Colour LED Strips and compatible with Foss FLDC1S Receivers.
- Individual Zone push button dimming control.
- RF wireless technology with a control distance of up to 30 metres.
- Pair each zone with one or multiple receivers
- CR2032 battery power.

Technical Parameters

- Output signal: RF(2.4GHz)
- Working voltage: 3VDC(CR2032)
- Working current: <5mA
- Standby current: <2µA
- Standby time: 2 years
- Remote distance up to 30m within Free Range. Please allow for 12m within areas restricted by obstacles.
- Working temperature: -30°C ~55°C
- Dimensions: L135×W40×H11mm
- Weight: 41g

Operation

Pull out the plastic battery plate from the battery compartment located on the bottom of the remote to replace.

Pairing Guide

Pairing your remote with each 2.4GHz RF receiver (FLDC1S) choose between two pairing methods.

- Using the "Match Key"

Match the controller with our receiver (Using the Match Key on the receiver)

1. Match: Short press the match key, then press the zone key on the remote within 5s.
2. To Delete a Match: Long press the match key on the receiver for 5s.

- At Power Up

Match the controller with our receiver (Without using the Match Key)

1. Match Switch off receiver power, then switch on power again, short press the zone key 3 times on the remote quickly within 5s after the receiver powers on, the link has been completed once the connected LED lights flash 3 times.
2. To Delete a match: Switch off power to the receiver, then switch on power again, short press the zone key you are deleting 5 times on the remote within 5s after power on, the unlink has been completed once the connected LED lights flash 5 times.

Key Functions



Dimensions

